## **CCD-4000UV**

## 4 MPixel High Resolution CCD Camera with increased UV-sensitivity



## **Features**

- 2048 (H) x 2048 (V) square pixels
- UV-sensitivity up to 190...200nm
- 7.5 frames/sec. at 2048 (H) x 2048 (V) pixels or 15 frames/sec. at 2048 (H) x 1024 (V) pixels
- Progressive scan
- Interline-transfer sensor (IT)
- Asynchronous shutter up to 1/10000 sec. (image on demand)
- Effective camera dynamics ≥ 1:1000 (≥ 60 dB)
- Digital RS-644 output with 12-bit
- Single output (40 Mpixel/sec.)



With an increased UV-sensitivity the **CCD-4000UV** is a further member of the VDS high resolution high fidelity CCD camera family.

Due to a special CCD as well as the use of quartz glass as input window, the camera offers a good sensitivity up to the 190...200 nm UV-area

The CCD-4000UV gives out the full resolution with 7.5 fps. In the binning mode 2048 (H) x 1024 (V) even 15 fps are reached.

By means of the progressive interline transfer sensor very short exposure times up to 1/10000 seconds can be achieved at a full resolution. The exposure time can be regulated in steps of approx. 64  $\mu s$ . Due to the asynchronous operation (image on demand), the exposure starts 15  $\mu s$  after an external trigger pulse. Therefore the camera is especially useful for recording moving objects.

The effective dynamic of the complete camera

 $D = \frac{Sat_{(count)} - Dark_{(count)}}{RMSNoise_{(count)}}$ 

is more than 1000 and therefore offers reserves even for difficult lighting conditions or very short exposure times.

The RS-644 (LVDS) digital output supplies image data with 12-bit precision.

Because of the C-mount connector different C-mount objectives and adaptors for F-mount can be used. The CCD-4000UV is identical in the mechanic and pin-to-pin compatible to the CCD-1300 camera line.


## **Technical Data**


- Resolution: 2048 (H) x 2048 (V) pixels
- Progressive scan
- Image rate: up to 7.5 frames/sec. (2048 x 2048) or up to 15 frames/sec. (2048 x 1024)
- Pixel size: 7.4 μm x 7.4 μm
- Active sensor size: 15.15 (H) mm x 15.15 (V) mm
- Interline transfer sensor (no mech. shutter required)
- Electronic shutter up to 1/10,000 sec.; adjustable in 64 µs steps
- Image on demand
- Effective dynamics: ≥ 1:1000 (≥ 60 dB)
- Sensor saturation: ≥ 40,000 e
- Anti-blooming circuit
- Exposure time up to approx. 1 sec.
- Digital output: 12-bit, RS-644 (LVDS)
- Frame system: 2082 lines
- Pixel clock: 40 MHz
- Video gain: 1 or 2 (+ 6 dB)
- Power supply: + 12 V (SELV), approx. 0.65 A
- Ambient air temperature: 0° to 40° C
- Lens mount: C-mount or F-mount with adaptor
- CE standard
- Made in Germany

| RS-644 Digital Output<br>(37-pin D-SUB Jack) |          |     |          |  |  |  |
|----------------------------------------------|----------|-----|----------|--|--|--|
| Pin                                          | Function | Pin | Function |  |  |  |
| 1                                            | PCLK     | 20  | /PCLK    |  |  |  |
| 2                                            | LEN      | 21  | /LEN     |  |  |  |
| 3                                            | FEN      | 22  | /FEN     |  |  |  |
| 4                                            | D0       | 23  | /D0      |  |  |  |
| 5                                            | D1       | 24  | /D1      |  |  |  |
| 6                                            | D2       | 25  | /D2      |  |  |  |
| 7                                            | D3       | 26  | /D3      |  |  |  |
| 8                                            | D4       | 27  | /D4      |  |  |  |
| 9                                            | D5       | 28  | /D5      |  |  |  |
| 10                                           | D6       | 29  | /D6      |  |  |  |
| 11                                           | D7       | 30  | /D7      |  |  |  |
| 12                                           | D8       | 31  | /D8      |  |  |  |
| 13                                           | D9       | 32  | /D9      |  |  |  |
| 14                                           | D10      | 33  | /D10     |  |  |  |
| 15                                           | D11      | 34  | /D11     |  |  |  |
| 16                                           | GND      | 35  | GND      |  |  |  |
| 17                                           | /TREX    | 36  | TREX     |  |  |  |
| 18                                           | /SV2     | 37  | Mode     |  |  |  |
| 19                                           | /BIN     |     |          |  |  |  |

| Power and Control Input<br>(15-pin D-SUB Jack) |                                          |                 |  |  |
|------------------------------------------------|------------------------------------------|-----------------|--|--|
| Pin                                            | Function                                 |                 |  |  |
| 1                                              | +12V DC                                  |                 |  |  |
| 2                                              |                                          |                 |  |  |
| 3                                              | GND                                      |                 |  |  |
| 4                                              |                                          |                 |  |  |
| 5                                              |                                          |                 |  |  |
| 6                                              |                                          |                 |  |  |
| 7                                              |                                          |                 |  |  |
| 8                                              |                                          |                 |  |  |
| 9                                              | Mode: (Open) → Continuous<br>(GND) → IOD |                 |  |  |
| 10                                             | -                                        | Trigger Input   |  |  |
| 11                                             | +                                        | (Opto Coupler)  |  |  |
| 12                                             | -                                        | Exposure Output |  |  |
| 13                                             | +                                        | (Opto Coupler)  |  |  |
| 14                                             | Line Sync Output                         |                 |  |  |
| 15                                             | Frame Sync Output                        |                 |  |  |

Spectral sensitivity





HIGH PERFORMANCE DIGITAL CAMERAS HIGH PERFORMANCE DIGITAL CAMERAS **HIGH PERFORMANCE DIGITAL CAMERAS**